

ROBUS®

SONICO LED HIGHBAY, IP65, 1-10V DIMMABLE, 1M FLEX AND PLUG, 5000K

RSN10050DA4-04 RSN12050DA4-04 RSN17050DA4-04

PLEASE READ INSTRUCTION BEFORE COMMENCING INSTALLATION AND RETAIN FOR FUTURE REFERENCES.

! Electrical products can cause death or injury, or damage to property. If in any doubt about the installation or use of this product, consult a competent electrician

Note:

Product technical information and specification may change over time without prior notification. For the latest technical information please visit our web site www.robus.com or robusdirect.com

-25°C < Ta < +45°C, 220-240V ~ 50/60Hz, Class I, IP65
Suitable for mounting on a normally flammable surface.

Installation

1. Ensure mains supply is switched off before commencing work.
 2. Choose suitable location for mounting the luminaire.
 3. Ensure that the area directly below is not obstructed by pipes, racking or structural building supports.
 4. If required change accessory as per list (see pictogram 2 and 3).
- Suspension Mounting (see pictogram 4):**
5. Screw eye hook into the hole on top of luminaire and insert screw to fix the hook so it is secure.
 6. Suspend the luminaire on the ceiling using a suitable hook.
- Surface Mounting (see pictogram 5):**
7. Attach bracket (RSNB-S or RSNB-L) to the luminaire.
 8. Mark appropriate fixing hole positions on the surface, check location buried cables, pipes and other building services before drilling.
 9. Drill holes for wall bolts, attach fitting to the surface and ensure it is secure.
 10. Adjust fitting to desired angle and tighten screws, ensure it is secure.
 11. Connect supply: Insert plug into the socket and connect 1-10V dimmable cables to dimmable system: (DIMM - and DIMM +). Alternatively connect supply cables: Brown to Live, Blue to Neutral and Green/Yellow to earth.

Accessories: Wire guard (pictogram 2), Lens (pictogram 3) and surface mounting brackets (pictogram 5).

RSNB4-S : Surface mounting brackets for 100W and 120W highbay

RSNB4-L : Surface mounting brackets for 170W highbay

Please purchase it separately if it were your need.

The Installation must be carried out by a qualified electrician

LED Group Australasia
9/210 Queensport Road North
Murarrie
QLD 4172
Australia

Tel: 07 3890 5444
Fax: 07 3890 4777
Email: purchases@robus.com
Website: www.robus.com.au

LED Group
Crowe Hogarth
72 Trafalgar Square
NELSON 7010
New Zealand

Tel: +64 0508 533 335
Email: nz_purchases@robus.com
Website: www.robusled.co.nz

